

ESD-TR-64-637

W06874/0000/01/0/00

FAST LOGIC CIRCUIT TEST ASSEMBLY

TECHNICAL REPORT NO. ESD-TR-64-637

ESD RECORD COPY

RETURN TO
SCIENTIFIC & TECHNICAL INFORMATION DIVISION
(ESTI), BUILDING 1211

DECEMBER 1965

ESD ACCESSION LISTESTI Call No. AL 48585Copy No. 1 of 1 cys.

J. Liu
N.S. Zimbel

Prepared for

COMPUTER DIVISION

DEPUTY FOR ENGINEERING AND TECHNOLOGY

ELECTRONIC SYSTEMS DIVISION

AIR FORCE SYSTEMS COMMAND

UNITED STATES AIR FORCE

L. G. Hanscom Field, Bedford, Massachusetts



Project 5080

Prepared by

THE MITRE CORPORATION
Bedford, Massachusetts
Contract AF19(628)-5165

ESRC

ADO 626191

Copies available at Clearing House for Federal Scientific and Technical Information (formerly Office of Technical Services).

Qualified requesters may obtain copies from DDC. Orders will be expedited if placed through the librarian or other person designated to request documents from DDC.

When US Government drawings, specifications, or other data are used for any purpose other than a definitely related government procurement operation, the government thereby incurs no responsibility nor any obligation whatsoever; and the fact that the government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise, as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

Do not return this copy. Retain or destroy.

ABSTRACT

This document describes the Fast Logic Circuit Test Assembly built to evaluate the system operating characteristics of nanosecond switching circuits which have been developed at The MITRE Corporation. The Test Assembly, which includes most of the classes of logic functions which might be encountered in a full scale serial or parallel computer, will also serve as a vehicle for evaluation of circuit reliability and for signal and power distribution methods.

The Test Assembly includes two serial registers which use electro-magnetic delay line storage. The shift registers, associated with these delay lines to implement the serial-to-parallel conversion or vice versa, shift at a 100-mc rate. Also included, in addition to a 100-mc counter and various control networks, is an 8-bit parallel adder which may be expanded using identical adder modules to form a 64-bit adder with 30-nanosecond addition time.

REVIEW AND APPROVAL

This technical report has been reviewed and is approved.


SEYMOUR JEFFERY
Major, USAF
Chief, Computer Division

CONTENTS

<u>SECTION</u>		<u>Page No.</u>
I	INTRODUCTION	1
II	GENERAL DESCRIPTION	3
	Normal Operations	3
	Manual Operations	7
III	DESCRIPTION OF FUNCTIONAL BLOCKS	8
	Registers P and A	8
	Adder	10
	Register Z	10
	Control Circuits	17
	Timing Networks	18
	Constant Register and Shift Control Network	18
	APPENDIX – Table I	A-1

ILLUSTRATIONS

<u>Figure</u>		<u>Page No.</u>
1	System Block Diagram	4
2	System Timing Chart	5
3	Logic Functions	9
4	Serial-to-Parallel Converter	11-12
5	Adder	13-14
6	Parallel-to-Serial Converter	15-16
7	Timing Networks	19-20
8	Timing Chart for Timing Network	21
9	Control Network Timing Chart-Natural Cycle	22
10	Constant Register	23-24
11	Shift Control Network	25-26

SECTION I

INTRODUCTION

The purpose of the Fast Logic Circuit Test Assembly is to evaluate the system operating characteristics of nanosecond switching circuits which have been developed at The MITRE Corporation. The test assembly includes most of the classes of logic functions which might be encountered in a full-scale, serial or parallel computer.

Specifically, the test assembly consists of a 48-bit-input serial register which communicates with a shift control network through an 8-bit, serial-to-parallel converter. The shift control network couples to an 8-bit, parallel adder, which in turn couples to an 8-bit, parallel-to-serial converter that is integral with a 48-bit, serial-output register. Appropriate control sequencing circuits are also included. Normal operation consists of two cycles: an add cycle followed by a subtract-and-compare cycle; 100% checking results.

The input and output registers use electromagnetic delay-line storage operating at a 50-mc clock rate (NRZ) which corresponds to a 100-mc information-bit rate.

The circuitry associated with the serial storage is synchronous and includes 8-bit shift registers which shift at a 100-mc rate. The shift registers implement the serial-to-parallel and parallel-to-serial conversions.

The 8-bit parallel adder is asynchronous and utilizes single-level, 4-bit, carry anticipation. Execution time is approximately 20 nanoseconds for an 8-bit addition. The adder modules may be used to build a 64-bit parallel adder with 30-nanosecond addition time (see page 10).

The test assembly will serve as a vehicle for evaluation of circuit reliability and methods for signal and power distribution. All electronic

components have been measured and catalogued for the purpose of correlating circuit performance during all phases of testing. Initially, the circuit components will be conventional, discrete, semiconductors and passive components mounted on printed circuit cards. There are nine logic cards and 268 circuit cards.

SECTION II

GENERAL DESCRIPTION

In the test assembly, except for the timing and control networks, the functional blocks used are those which are commonly used in general-purpose digital systems. Certain of these functional blocks, in either 4-bit or 8-bit parallel form, are designed for maximum operating speed, although no particular effort was made to obtain savings in hardware. The serial one-word registers and conversion registers are also essential elements of a serially organized computer.

Figure 1 is the system block diagram; Figure 2 is a timing chart.

NORMAL OPERATIONS

The shift register P, which is a part of the 48-bit-input, serial register, converts serial information to 8-bit, parallel form in addition to receiving input information in 8-bit parallel blocks during the input phase, IN. The output register Z, is used to obtain parallel-to-serial conversion. P and Z are simple shift registers.

The natural cycles of the system have a period of 144 clock times (3 times 48 bit times). During the first 48 bit-times, T1, the 8-bit, parallel information block in Register P (bits P_0 through P_7) is strobed into Register A at the zeroth bit time, $T^0 \cdot t_0 \pmod{8}$ and becomes block $\{A_0 \dots A_7\}$. At the output of Register A, this information $\{A_0 \dots A_7\}$, is transferred to an 8-bit, parallel adder through one of the three paths on the shift control network. The path taken depends on whether a one-bit, toggle switch, control register, CR, is one or zero.

If CR is equal to one, then the eight bits of information are transferred to the adder and added to a constant stored in the 8-bit toggle switch register.




Figure 1. System Block Diagram




Figure 2. System Timing Chart

At time $T^0 \cdot t_7 \pmod{8}$, the last bit time in the block time, the result from the adder (modified information) is transferred into the output register, Z, where it is converted back to serial form, and stored in the output 48-bit serial register. At the next zeroth bit time, $T^1 \cdot t_0 \pmod{8}$, the next information block (bits P_8 through P_{15}) in Register P is transferred to Register A and a similar operation is again performed.

If CR content is zero, the information bits are first end-shifted left one position $\{A_1 \dots A_7, A_0\}$ before being transferred to the adder for a zero addition. The control register CR must be set before system operation is started. The contents of the registers at each $t_0 \pmod{8}$ is shown in the system timing chart, Figure 2. At the last bit time in this phase, $T^5 \cdot t_7 \pmod{8} = t_{47}$, the register TIME in the control network is set and the system goes into the second operation phase, T2.

T2 actually lasts 52 bit-times. During the first 8-bit time, T^0 , the system is "idling." At the 8th-bit time of this idling period, the timing circuit is reset to $T^0 \cdot t_0 \pmod{8}$ and the first 8-bit modified information block $\{Z_0 \dots Z_7\}$ in Register Z is strobed into the storage register — Register A.

In this phase, if control register CR is equal to one, the content of the constant register is subtracted from the information $\{A'_0 \dots A'_7\}$ passing through the adder. The subtraction is done by adding the 2's complement of the constant to the operand A' . The result from the adder is strobed into Register Z at $T^0 \cdot t_7 \pmod{8}$. The next information block $\{Z_8 \dots Z_{15}\}$ is strobed into Register A at the same time. At time $T^1 \cdot t_0 \pmod{8}$, the information in Register Z is equal to the corresponding 8-bit block in Register P (See Figure 2).

If CR is equal to zero, the eight bits of information are cycled right one position $\{A_7, A_0 \dots A_6\}$ before the 8-bit block reaches the adder, and the constant is again zero. At the end of phase T2, $T^5 \cdot t_7 \pmod{8}$, reset Register RE and the reset phase starts. In this period, zeros are fed into output Register Z and the content of Register P is not changed.

MANUAL CONTROLS

If at any time during T1, the information-hold switch is turned on, the system will stay in the phase T1 until the switch is turned off, whereupon the system will continue its normal operation as described above. If the switch is turned on during other phases of operation, the system will go through the natural cycle until phase T1 is reached. It will then remain in phase T1 until the switch is turned off.

After Master Reset Time, the system starts its natural cycle when the start pushbutton is activated. Before the first manual phase, information may be transferred in 8-bit parallel form into the input Register P. This period during which the register IN is in "one" state is called the "input" phase.

SECTION III

DESCRIPTION OF FUNCTIONAL BLOCKS

The test assembly will be built with logic boards, each of which may mount 70 logic circuits that perform logic functions described in Figure 3. The logic boards used in the system are listed in Table I. The input and output signals to and from these logic boards are levels (as contrasted to pulses).

The following logical equations describe each of the functional blocks used:

1. Registers P and A (Figure 4)

Let

$$F = T1 \cdot C \cdot \overline{IN} \cdot t_0 \pmod{8}$$

$$G = T2 \cdot C \cdot \overline{Q} \cdot t_7 \pmod{8}$$

then

$$S_{P_i} = P_{i+1} \cdot C \oplus U_i(1) \cdot \text{strobe}$$














$$R_{P_i} = \overline{P}_{i+1} \cdot C \oplus U_i(0) \cdot \text{strobe}$$

$$S_{A_i} = P_i \cdot F \oplus Z_{i+1} \cdot G$$

$$R_{A_i} = \overline{P}_i \cdot F \oplus \overline{Z}_{i+1} \cdot G$$

where

$$i = 0, 1, \dots, 7$$

LOGIC FUNCTIONS	LOGIC SYMBOL	TYPES OF CIRCUIT USED	FAN IN FAN OUT	REMARKS
AND "•"	 $F = \prod_{i=1}^5 A_i$	DITEG	FAN IN = 5 FAN OUT = 8	1. 2 GATES PER PACKAGE 2. THESE TYPES OF AND GATES MUST BE USED IN THE FOLLOWING LOGIC CONFIGURATIONS: A.  B.  C.  OR THE POSITION MARKED WITH THE SIGN "*" D. 
	 $F = \prod_{i=1}^3 A_i$	SIDEL	FAN IN = 3 FAN OUT = 8 (TWO TRANSMISSION LINES)	2 CIRCUIT PER PACKAGE
FLIP-FLOP		UNIVER I	EACH SIDE OF FLIP-FLOP CAN DRIVE TWO TRAN. LINES (8 AND GATES)	1 CIRCUIT PER PACKAGE
INVERSION		UNIVER I	OUTPUT CAN DRIVE TWO TRANSMISSION LINES	2 CIRCUIT PER PACKAGE
OR "+"	 $F = \sum_{i=1}^4 A_i$	ALTG	FAN IN = 4 FAN OUT = 8 (TWO TRAN. LINES)	1 CIRCUIT PER PACKAGE
BUFFER OR "+"	 $F = R_1 \oplus R_2 \oplus \dots \oplus R_i \quad i \leq 4$			THIS FUNCTION IS ACCOMPLISHED BY WIRING BY WIRING THE OUTPUTS OF AND GATES OR OR GATES TOGETHER
AMPLIFICATION INVERTER		UNIVER II	EACH OUTPUT CAN DRIVE TWO TRAN. LINES (8 AND OR OR GATE)	1 CIRCUIT PER PACKAGE
AMPLIFICATION EITHER BOTH + OR BOTH -		UNIVER	EACH OUTPUT CAN DRIVE TWO TRAN. LINES (8 AND OR OR GATES)	1 CIRCUIT PER PACKAGE
DELAY		DELAY LINES		

10-17,932

Figure 3. Logic Functions

2. Adder (Figure 5)

Let

$$D_i = A_i \cdot B_i; \quad T_i = \bar{A}_i B_i \oplus \bar{B}_i A_i$$

where

$$i = 0, 1, \dots, 3$$

$$C_1 = D_0 \oplus T_0 \cdot C_0$$

$$C_2 = D_1 \oplus T_1 \cdot D_0 \oplus T_1 \cdot T_0 \cdot C_0$$

$$C_3 = D_2 \oplus T_2 \cdot D_1 \oplus T_2 \cdot T_1 \cdot D_0 \oplus T_2 \cdot T_1 \cdot T_0 \cdot C_0$$

$$D_G = D_3 \oplus T_3 \cdot D_2 \oplus T_3 \cdot T_2 \cdot D_1 \oplus T_3 \cdot T_2 \cdot T_1 \cdot D_0$$

$$T_G = T_0 \cdot T_1 \cdot T_2 \cdot T_3$$

$$RS_i = T_i \bar{C}_i \oplus \bar{T}_i C_i$$

This 4-bit adder module was designed to achieve maximum speed when it is grouped with other identical modules to form a parallel adder which is capable of adding two 64-bit binary numbers in 30 nanoseconds (12 stage delays). For detailed design information, see Fast Circuit Design Note, JL-1.

3. Register Z (Figure 6)

Let

$$F = \bar{Q} \cdot C \cdot t_7 \pmod{8}$$

Set

$$Z_i = Z_{i+1} \cdot C \oplus RS_i \cdot F$$

$$R_{Z_i} = \overline{Z_{i+1}} \cdot C \oplus RS_1 \cdot F$$




Figure 4. Serial-to-Parallel Converter




Figure 5. Adder




Figure 6. Parallel-to-Serial Converter

$$\text{ERROR} = C \cdot Z_0 \cdot \overline{P}_{-16} \cdot \text{comp} \oplus C \cdot \text{comp} \cdot \overline{Z}_0 \cdot P_{-16}$$

4. Control Circuits

Let

$$\text{NO} = \overline{\text{IN}} \cdot \overline{\text{CH}}$$

$$\text{S}_{\text{TIME}} = t_{47} \cdot C \cdot \text{NO} \cdot \overline{\text{RE}} \cdot \overline{\text{TIME}}$$

$$\text{R}_{\text{TIME}} = t_{47} \cdot C \cdot \overline{\text{IN}} \cdot \overline{\text{RE}} \cdot \text{TIME} \oplus \text{MR}$$

$$\text{T1} = (\overline{\text{TIME}}) \cdot (\text{RE})$$

$$\text{T2} = (\text{TIME}) \cdot (\text{RE})$$

$$\text{S}_{\text{Q}} = \text{T1} \cdot \text{N0} \cdot (t_{47} \cdot C)$$

$$\text{R}_{\text{Q}} = \text{Q} \cdot (t_7 \pmod{8}) \cdot C \oplus \text{MR}$$

$$\text{S}_{\text{RE}} = t_{47} \cdot C \cdot \text{T2}$$

$$\text{R}_{\text{RE}} = \text{MR} \oplus \text{RE} \cdot (t_{47} \cdot C)$$

$$\text{S}_{\text{I}} = (t_{47} \cdot C) \cdot \overline{\text{I}}$$

$$\text{R}_{\text{I}} = \text{MR}$$

$$\text{S}_{\text{IN}} = \text{MR}$$

$$\text{R}_{\text{IN}} = \text{IN} \cdot \text{I} \cdot (t_{47} \cdot C)$$

$$\text{S}_{\text{comp}} = \text{T2} \cdot (t_7 \pmod{8}) \cdot \overline{\text{Q}} \cdot C$$

$$\text{R}_{\text{comp}} = t_7 \pmod{8} \cdot \text{RE} \cdot C \oplus \text{MR}$$

5. Timing Networks (Figures 7, 8, 9)

Counter L

$$S_{L_0} = \bar{L}_0 \cdot C \oplus MR$$

$$R_{L_0} = L_0 \cdot C$$

$$S_{L_1} = \bar{L}_1 \cdot L_0 \cdot C \oplus MR$$

$$R_{L_1} = L_1 \cdot L_0 \cdot C$$

$$S_{L_2} = \bar{L}_2 \cdot L_1 \cdot (\bar{L}_0) \cdot C \oplus MR$$

$$R_{L_2} = L_2 \cdot L_1 \cdot (\bar{L}_0) \cdot C$$

$$T_0(\text{mod } 8) = \bar{L}_0 \cdot \bar{L}_1 \cdot \bar{L}_2$$

$$T_7(\text{mod } 8) = L_0 \cdot L_1 \cdot L_2$$

$$t_{47} = L_0 \cdot L_1 \cdot L_2 \cdot M_0 \cdot M_2$$

Counter M

$$\text{Let } F = L_2 \cdot L_1 \cdot L_0 \cdot \bar{t}_{47} \cdot \bar{Q}$$

$$S_{M_0} = \bar{M}_0 \cdot C \cdot F \oplus MR \oplus RE \cdot \text{Reset} \cdot C$$

$$R_{M_0} = M_0 \cdot C \cdot F \oplus \text{Reset} \cdot C \cdot \overline{RE}$$

$$S_{M_1} = \bar{M}_1 \cdot M_0 \cdot C \cdot F$$

$$R_{M_1} = M_1 \cdot M_0 \cdot C \cdot F \oplus \text{Reset} \cdot C$$

$$S_{M_2} = \bar{M}_2 \cdot M_1 \cdot M_0 \cdot C \cdot F \oplus MR$$

$$R_{M_2} = M_2 \cdot M_1 \cdot M_0 \cdot C \cdot F \oplus \text{Reset} \cdot C$$

$$\text{Reset} = M_0 \cdot M_2 \cdot G \oplus M_0 \cdot \bar{M}_1 \cdot M_2 \cdot \bar{Q}$$

6. Constant Register (Figure 10) and Shift Control Networks (Figure 11)

$$B_i = CR \cdot T1 \cdot CT_i$$

where

$$i = 0, 1, 2, \dots, 7$$

$$\bar{B}_i = CR \cdot T2 \cdot \overline{CT_i}$$




Figure 7. Timing Networks




Figure 8. Timing Chart for Timing Network

Figure 9. Control Network Timing Chart-Natural Cycle




Figure 10. Constant Register

ID-17, 324




Figure 11. Shift Control Network

$$A'_i = A_i \cdot CR \oplus \overline{CR} \cdot T1 \cdot A_{i+1} \oplus \overline{CR} \cdot T2 \cdot A_{i-1}$$

for

$$i = 0, 1, \dots, 7$$

and the addition or subtraction of subscribed is in mod 8

$$A'_i = A_i \cdot CR + \overline{CR} \cdot T1 \cdot A_{i+1} \oplus \overline{CR} \cdot T2 \cdot A_{i-1}$$

TABLE I

Functional Blocks Description	Adder	Parallel-To-Serial Converter S Registers	SRI Serial-To-Parallel Converter P&A Register	Constant Register & Shift Control Network	System Operation Control	Timing Network	Misc.
UNIVER I	6	8	8	8	7	12	5
UNIVER II	6			5	1	4	
PDA		3	3		3	3	
Board PDA		1	1		1	1	
DITEG and Gate	19	19	18	20	9	13	5
SIDEL					2	2	
2-Nanosecond Delays		16	8		11	13	
OR Gate							1
Register Packages	25	25	25	25	25	25	
No. of Boards Req. in the System	2	1	2	1	1	1	
Logical Diagram	Fig. 5	Fig. 6	Fig. 4	Fig. 10, 11		Fig. 7	

DOCUMENT CONTROL DATA - R&D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1. ORIGINATING ACTIVITY (Corporate author) The MITRE Corporation Bedford, Mass.		2a. REPORT SECURITY CLASSIFICATION Unclassified	
		2b. GROUP N/A	
3. REPORT TITLE Fast Logic Circuit Test Assembly			
4. DESCRIPTIVE NOTES (Type of report and inclusive dates) N/A			
5. AUTHOR(S) (Last name, first name, initial) Liu, Jane, and Zimbel, Norman S.			
6. REPORT DATE December 1965		7a. TOTAL NO. OF PAGES 28	7b. NO. OF REFS
8a. CONTRACT OR GRANT NO.		8a. ORIGINATOR'S REPORT NUMBER(S) ESD-TDR-64-637	
b. PROJECT NO.		8b. OTHER REPORT NO(S) (Any other numbers that may be assigned this report) W-6874/0000/01/0/00	
c.			
d.			
10. AVAILABILITY/LIMITATION NOTICES Qualified requesters may obtain from DDC. DDC release to CFSTI authorized.			
11. SUPPLEMENTARY NOTES		12. SPONSORING MILITARY ACTIVITY Electronics Systems Division L. G. Hanscom Field, Bedford, Mass.	
13. ABSTRACT <p>This document describes the Fast Logic Circuit Test Assembly built to evaluate the system operating characteristics of nanosecond switching circuits which have been developed at The MITRE Corporation. The Test Assembly, which includes most of the classes of logic functions which might be encountered in a full scale serial or parallel computer, will also serve as a vehicle for evaluation of circuit reliability and for signal and power distribution methods.</p> <p>The Test Assembly includes two serial registers which use electromagnetic delay line storage. The shift registers, associated with these delay lines to implement the serial-to-parallel conversion or vice versa, shift at a 100-mc rate. Also included, in addition to a 100-mc counter and various control networks, is an 8-bit parallel adder which may be expanded using identical adder modules to form a 64-bit adder with 30-nanosecond addition time.</p>			

14

KEY WORDS

LINK A

ROLE

WT

LINK B

ROLE

WT

LINK C

ROLE

WT

Computer logic
 Logic circuits
 Digital computer
 Serial computer
 Parallel computer
 Serial-to-parallel conversion
 Parallel-to-serial conversion

INSTRUCTIONS

1. **ORIGINATING ACTIVITY:** Enter the name and address of the contractor, subcontractor, grantee, Department of Defense activity or other organization (*corporate author*) issuing the report.

2a. **REPORT SECURITY CLASSIFICATION:** Enter the overall security classification of the report. Indicate whether "Restricted Data" is included. Marking is to be in accordance with appropriate security regulations.

2b. **GROUP:** Automatic downgrading is specified in DoD Directive 5200.10 and Armed Forces Industrial Manual. Enter the group number. Also, when applicable, show that optional markings have been used for Group 3 and Group 4 as authorized.

3. **REPORT TITLE:** Enter the complete report title in all capital letters. Titles in all cases should be unclassified. If a meaningful title cannot be selected without classification, show title classification in all capitals in parenthesis immediately following the title.

4. **DESCRIPTIVE NOTES:** If appropriate, enter the type of report, e.g., interim, progress, summary, annual, or final. Give the inclusive dates when a specific reporting period is covered.

5. **AUTHOR(S):** Enter the name(s) of author(s) as shown on or in the report. Enter last name, first name, middle initial. If military, show rank and branch of service. The name of the principal author is an absolute minimum requirement.

6. **REPORT DATE:** Enter the date of the report as day, month, year, or month, year. If more than one date appears on the report, use date of publication.

7a. **TOTAL NUMBER OF PAGES:** The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.

7b. **NUMBER OF REFERENCES:** Enter the total number of references cited in the report.

8a. **CONTRACT OR GRANT NUMBER:** If appropriate, enter the applicable number of the contract or grant under which the report was written.

8b, 8c, & 8d. **PROJECT NUMBER:** Enter the appropriate military department identification, such as project number, subproject number, system numbers, task number, etc.

9a. **ORIGINATOR'S REPORT NUMBER(S):** Enter the official report number by which the document will be identified and controlled by the originating activity. This number must be unique to this report.

9b. **OTHER REPORT NUMBER(S):** If the report has been assigned any other report numbers (*either by the originator or by the sponsor*), also enter this number(s).

10. **AVAILABILITY/LIMITATION NOTICES:** Enter any limitations on further dissemination of the report, other than those

imposed by security classification, using standard statements such as:

- (1) "Qualified requesters may obtain copies of this report from DDC."
- (2) "Foreign announcement and dissemination of this report by DDC is not authorized."
- (3) "U. S. Government agencies may obtain copies of this report directly from DDC. Other qualified DDC users shall request through _____."
- (4) "U. S. military agencies may obtain copies of this report directly from DDC. Other qualified users shall request through _____."
- (5) "All distribution of this report is controlled. Qualified DDC users shall request through _____."

If the report has been furnished to the Office of Technical Services, Department of Commerce, for sale to the public, indicate this fact and enter the price, if known.

11. **SUPPLEMENTARY NOTES:** Use for additional explanatory notes.

12. **SPONSORING MILITARY ACTIVITY:** Enter the name of the departmental project office or laboratory sponsoring (*paying for*) the research and development. Include address.

13. **ABSTRACT:** Enter an abstract giving a brief and factual summary of the document indicative of the report, even though it may also appear elsewhere in the body of the technical report. If additional space is required, a continuation sheet shall be attached.

It is highly desirable that the abstract of classified reports be unclassified. Each paragraph of the abstract shall end with an indication of the military security classification of the information in the paragraph, represented as (TS), (S), (C), or (U).

There is no limitation on the length of the abstract. However, the suggested length is from 150 to 225 words.

14. **KEY WORDS:** Key words are technically meaningful terms or short phrases that characterize a report and may be used as index entries for cataloging the report. Key words must be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context. The assignment of links, rules, and weights is optional.